

Phone: (405) 224-4046 Fax: (405) 224-9423 Email: Info@HSISensing.com Web: www.hsisensing.com Address: 3100 Norge Road, Chickasha, OK 73018

Item Number HSR-0025R Series Contact Form

Α

Switch Configuration <u>SPST</u> Rev. <u>D</u>

World's Smallest and Most Sensitive Magnetically Operated Reed Switch			
Features	Advantages		
World's smallest reed switch	Maximum sensitivity in a miniature size		
 Hermetically sealed Rhodium contacts 	Hi-Rel versions available		
 Materials are Lead free and RoHS compliant 	Not ESD sensitive		
	 Ideal for proximity sensors and reed relays 		

Electrical Specifications

Power		Watts - maximum	0.5
Voltage	Switching	VDC - maximum	30
	Breakdown	VDC - minimum	100
Current	Switching	Amp - maximum	0.01
	Carry	Amp - maximum	0.7
Resistance	Initial Contact Resistance	Ohm - maximum	0.75
	Insulation Resistance	Ohm - minimum	1 E11
Capacitance	Contact	pF - typical	0.7
Temperature	Operating	0°C	-40 to +125
	Storage	°C ♦	-40 to +200

Magn	etic	Specificatio	ns 💊

Pull - In Range	Ampere Turns	4-15		
Test Coil	NARM RS-421-A	Coil I		
Disaster 10 second to set the set for set the set				

Physical/Operational Specifications

Capsule Volume	Excluding Leads	CC - nominal	0.004
Contact Material			Rhodium
Operate Time	Including Bounce	mSeconds - maximum	0.30
Release Time		mSeconds - maximum	0.20



Notes:

(1) Specifications are not constant across entire magnetic range.

(2) Customer must exercise care in handling, mounting, lead forming, and cutting to prevent damage to glass capsule and/or switch sensitivity.

- (3) For information about performance, custom configurations, mounting options or packaging contact our Sales department.
- (4) Information contained hereon is for informational purposes only and should not be deemed as accurate for a specific application. Consult factory for specific application information and/or latest revision.