

## Phone: (405) 224-4046 Fax: (405) 224-9423 Email: Info@HSISensing.com Web: www.hsisensing.com Address: 3100 Norge Road, Chickasha, OK 73018

Item Number\_HSR-042R Series Contact Form A

Switch Configuration <u>SPST</u> Rev. <u>E</u>

Form A Miniature Switch			
Features	Advantages		
Hermetically sealed Rhodium contacts	Extended operations in extreme environments		
<ul> <li>Materials are Lead free and RoHS compliant</li> </ul>	Not ESD sensitive		
Industry Standard Size	Exceptional performance in magnetic proximity applications		
Offset gap construction			

## **Electrical Specifications**

Power		Watts - maximum	4
Voltage	Switching	VDC - maximum	100
	Breakdown	VDC - minimum	200
Current	Switching	Amp - maximum	0.2
	Carry	Amp - maximum	2.0
Resistance	Initial Contact Resistance	Ohm - maximum	0.20
	Insulation Resistance	Ohm - minimum	1 E11
Capacitance	Contact	pF - typical	0.8
Temperature	Operating	°C	-40 to+125
	Storage	°C	-40 to +200
	Magnetic Spe	cifications	
Pull - In Range		Ampere Turns	10-35
Test Coil		NARM RS-421-A	Coil I
	Physical/Operation	al Specifications	
Capsule Volume	Excluding Leads	CC - nominal	0.04
Contact Material			Rhodium
Operate Time	Including Bounce	mSeconds - maximum	0.60
Release Time		mSeconds - maximum	0.10
Ø.016in [0.41mm] —	Ø.090in [2.29mm] .360in± [9.14mm] 1.890in± [48.01mm]	±0.25]	Ø.023in [.58mm]

## Notes:

- (1) Specifications are not constant across entire magnetic range.
- (2) Customer must exercise care in handling, mounting, lead forming, and cutting to prevent damage to glass capsule and/or switch sensitivity.
- (3) For custom configurations or information about performance, mounting options or packaging, contact our Sales department.
- (4) Information contained hereon is for informational purposes only and should not be deemed as accurate for a specific application. Consult factory for specific application information and/or latest revision.