

Phone: (405) 224-4046 Fax: (405) 224-9423 Email: Info@HSISensing.com Web: www.hsisensing.com Address: 3100 Norge Road, Chickasha, OK 73018

Item Number HSR-1016R Series Contact Form A

A Switch Configuration SPST Rev. B

| Form A Miniature Reed Switch  |  |  |  |
|---|--|--|--|
| Features  | Advantages   |  |  |
| <ul> <li>Hermetically sealed contacts</li> <li>Unique blade design and surface finish</li> <li>Switch materials are Lead free and RoHS compliant</li> </ul> | <ul> <li>Extended operation in extreme environments</li> <li>Not ESD sensitive</li> <li>Ideal for proximity sensors and reed relays</li> </ul> |  |  |

## **Electrical Specifications**

| Power       |                            | Watts - maximum | 10          |
|-------------|----------------------------|-----------------|-------------|
| Voltage     | Switching                  | VDC - maximum   | 200         |
|             | Breakdown                  | VDC - minimum   | 400         |
| Current     | Switching                  | Amp - maximum   | 0.5         |
|             | Carry                      | Amp - maximum   | 1.5         |
| Resistance  | Initial Contact Resistance | Ohm - maximum   | 0.15        |
|             | Insulation Resistance      | Ohm - minimum   | 1 E11       |
| Capacitance | Contact                    | pF - typical    | 0.9         |
| Temperature | Operating                  | °C - maximum    | -40 to +125 |
|             | Storage                    | °C              | -40 to +200 |

## Magnetic Specifications

| Pull - In Range | Ampere Turns  | 15-40   |
|-----------------|---------------|---------|
| Test Coil       | NARM RS-421-A | Coil II |

## Physical/Operational Specifications

| Capsule Volume   | Excluding Leads  |    | CC - nominal       | 0.1     |
|------------------|------------------|----|--------------------|---------|
| Contact Material |                  |    |                    | Rhodium |
| Operate Time     | Including Bounce |    | mSeconds - maximum | 0.70    |
| Release Time     |                  | 24 | mSeconds - maximum | 0.20    |



## Notes:

- (1) Specifications are not constant across entire magnetic range.
- (2) Customer must exercise care in handling, mounting, lead forming, and cutting to prevent damage to glass capsule and/or switch sensitivity.
- (3) For information or custom configurations about performance, mounting options or packaging, contact our Sales department.
- (4) Information contained hereon is for informational purposes only and should not be deemed as accurate for a specific application. Consult factory for specific application information and/or latest revision.